

Short Circuit Ratings

	CA9-116	CA9-146	CA9-190	CA9-205	CA9-265	CA9-305	CA9-370	CA9-400	CA9-460	CA9-580	CA9-750	CA9-860	CA9-1060	CA9-1260	CA9-2050	CA9-2650
--	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	----------	----------	----------	----------

Short Circuit Coordination (Max. Fuse or Circuit Breaker Rating)
per IEC 60947-4-1

DIN Fuses -gG																	100 kA Available Fault Current																
Type "2" (400V)	[A]	250	250	315	315	400	500	630	630	630	800	800	1000	1250	~	~	~																
DIN Fuses -gG																	80 kA Available Fault Current																
Type "2" (690V)	[A]	160	200	315	315	400	425	500	500	630	800	800	1000	1600	~	~	~																
MCCB																	70 kA Available Fault Current																
Type "2" (400V)	[A]	160	160	320	320	400	630	630	630	630	800	1000	1600	1600	~	~	~																

Short Circuit Coordination (Max. Fuse or Circuit Breaker Rating)
per UL 60947 and CSA 22.2 No. 14 (contactor and fuses or circuit breaker only)

UL Class RK5 Fuses																	10 kA Available Fault Current																
Type 1 Combination (600V)	[A]	250	250	400	400	~	~	~	~	~	~	~	~	~	~	~	~																
UL Class J and CSA HRCI-J Fuses																	82 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	600	600	1200	1200	~	~	~	~	~																
UL Class J and CSA HRCI-J Fuses																	100 kA Available Fault Current																
Type 1 Combination (600V)	[A]	250	250	400	400	600	600	800	600	600	~	~	~	~	~	~	~																
Type 2 Combination (600V)	[A]	200	200	400	400	600	600	600	600	600	~	~	~	~	~	~	~																
UL Class L Fuses																	18 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	800	800	800	~	~	~	~	~	~	~	~	~																
UL Class L Fuses																	30 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	1000	1000	~	~	~	~	~	~	~																
UL Class L Fuses																	85 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	~	~	~	~	1600	1600	~	~	~																
UL Class L Fuses																	100 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	800	800	1200	1200	~	~	1600	~	~																
Type 2 Combination (600V)	[A]	~	~	~	~	~	~	~	~	~	1200	1200	~	~	~	~	~																
UL Inverse-Time Circuit																	42 kA Available Fault Current																
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	~	~	1200	1200	~	~	~	~	~																
UL Inverse-Time Circuit																	65 kA Available Fault Current																
Type 1 Combination (480V)	[A]	250	250	400	400	800	800	800	800	800	800	800	~	~	~	~	~																
UL Inverse-Time Circuit																	84 kA Available Fault Current																
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	600	800	~	~	~	~	~	~	~																
UL Inverse-Time Circuit																	89 kA Available Fault Current																
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	~	~	800	800	~	~	~	~	~																
UL Inverse-Time Circuit																	100 kA Available Fault Current																
Type 1 Combination (480V)	[A]	250	250	400	400	800	800	800	~	~	~	~	~	~	~	~	~																
UL Inverse-Time Circuit																	25 kA Available Fault Current																
Type 2 Combination (600V)	[A]	250	250	~	~	~	~	~	~	~	~	~	~	~	~	~	~																
UL Inverse-Time Circuit																	35 kA Available Fault Current																
Type 2 Combination (600V)	[A]	~	~	400	400	800	800	800	600	800	800	800	~	~	~	~	~																
UL Inverse-Time Circuit																	42 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	~	~	800	800	800	600	800	800	800	~	~	~	~	~																
UL Inverse-Time Circuit																	50 kA Available Fault Current																
Type 1 Combination (600V)	[A]	250	250	~	~	~	~	~	~	~	800	800	~	~	~	~	~																
UL Inverse-Time Circuit																	65 kA Available Fault Current																
Type 1 Combination (600V)	[A]	~	~	400	400	400	400	400	~	~	~	~	~	~	~	~	~																